

BEM:RSP — OS/3

Instruction Summary

Code Card

SPERRY  **UNIVAC**
COMPUTER SYSTEMS

UA-0244

The BEM programs described in this document are confidential information and proprietary products of the Sperry Univac Division.

This document contains the latest information available at the time of publication. However, Sperry Univac reserves the right to modify or revise its contents. To ensure that you have the most recent information, contact your local Sperry Univac representative.

SPERRY UNIVAC NEWSCOMP Newspaper Composition Program was used by Application Services in typesetting this publication.

Sperry Univac is a division of Sperry Rand Corporation.

AccuScan, FASTRAND, PAGEWRITER, SPERRY UNIVAC, UNISCOPE, UNISERVO, and UNIVAC are trademarks of Sperry Rand Corporation.

©1977 — Sperry Rand Corporation

Printed in U.S.A.

OS/3 BEM:RSP SUMMARY

BEM COMMANDS

| Command | Function |
|--|---|
| <u>/LOGON</u> id | Identifies the user to the system. Must always be the first command entered. The system will respond with a bulletin followed by: USER LOGGED ON, BEM SYSTEM READY |
| <u>/PRINT</u> (file parameters) | Prints a library element at the central site. |
| <u>/PUNCH</u> (file parameters) | Punches a library element at the central site. |
| <u>/FSTAT</u> Library (password), volume | Displays the directory of the requested file. |
| <u>/DELETE</u> (file parameters) | Deletes an element from a library file. |
| <u>/STATUS</u> <u>TERM</u> | Displays a list of terminals currently in use on the system. |
| <u>/STATUS</u> <u>RESOURCES</u> | Displays the amount of memory and disk space available to BEM. |
| <u>/EXEC</u> <u>RSP</u> | Invokes the Remote Spool Processor. When loaded the major command frame is displayed. |
| <u>/PAUSE</u> question | Displays the user's question on the 90/30 console and pauses the user until the operator's reply is available for display to the user. |
| <u>/TYPE</u> message | Displays the user's message on the 90/30 operator's console. |
| <u>/HELP</u> | Displays additional information about the previous error message. |
| <u>/LOGOFF</u> | Terminates a user's session and releases all work space to the system. |
| <u>/DISPLAY</u> <u>JOB</u> | Displays information about currently active batch jobs. |
| <u>/DISPLAY</u> <u>VOLUMES</u> | Displays the name of any disk packs mounted at the main site. |

DISPLAY COMMAND MODE

| Command | Function |
|---------------------|---|
| CMD | Return to major frame command mode. |
| UP <i>n</i> | Scroll screen up <i>n</i> lines. |
| DO <i>n</i> | Scroll screen down <i>n</i> lines. |
| RI <i>n</i> | Shift screen right <i>n</i> columns. |
| LE <i>n</i> | Shift screen left <i>n</i> columns. |
| DEL <i>n</i> | Delete <i>n</i> lines starting with the top line on the screen. |
| INS <i>n</i> | Insert <i>n</i> blank lines at the top of the screen. |
| UPD <i>n</i> | Update the top <i>n</i> lines on the screen. |
| <i>n.m</i> | Refresh the screen starting at line number <i>n</i> , column <i>m</i> . |
| null | Refresh the screen from the current position. |

SPOOL FILE DESCRIPTION SCREEN

| Field | |
|-------------------|--|
| JOB NAME | Job name of Spool file elements to be accessed. |
| ACCOUNT | Account number of Spool file element. |
| PROGRAM | Name of program which created Spool file element. |
| STEP | Job step number during which Spool file element was created. |
| LFD | Logical file name associated with Spool file element. |
| LABEL | Physical file name of Spool file element (JOB.LFD for reader files). |
| TYPE | Spool file queue to access LOG, PRINT, PUNCH, READER, JCS, RBPPR, and RBPPU. |
| JOB NUMBER | Sequential job number assigned by OS/3. |
| HELD | Y indicates Spool file held by // SPL HOLD or // SPL RETAIN. N indicates not held. |